

PAT 50A

ESD 50 Ω Calibration Attenuator for EFT / Burst Generators

■ IEC 61000-4-4 describes calibration of an EFT generator having 50 ohm high voltage output. The high voltage output is coupled through a 50 ohm attenuator and viewed on an oscilloscope or similar instrument having a bandwidth of at least 400MHz.



FEATURES

- Bandwidth **400MHz**
- Regular **BNC connection** to oscilloscope
- Designed for **8kV EFT** voltage

APPLICATIONS

Calibration of EFT/Burst Generators

OPTIONS & ACCESSORIES

- Verification 1 Adapter Schuko to 3 SHV BNC connectors. Fits in single phase CDN output to enable verification of EFT parameters through the CDN using 50 ohm attenuator.
- Verification 3 Adapter 5 x 4mm banana to 5 SHV BNC connectors. Fits to three phase CDN (FPEFT 32.1) to enable verification of EFT parameters through the CDN using the 50 ohm attenuator.

SCOPE OF SUPPLY

- Qty. 1 50 ohm attenuator
Qty. 1 Calibration certificate

TECHNICAL SPECIFICATIONS

EFT Impulse Range	0 – 8kV
Impedance	50 Ohms ± 2%
EFT Connection	SHV BNC, rated to 8kV

Frequency band	400MHz
Attenuation	54 dB
Voltage output	BNC, 50 ohm

Weight and Dimensions

50 ohm atten	120 x 25 x 25 mm (W x H x D)	0.1 kg (Net Weight)
--------------	------------------------------	---------------------

OFFICES:

Europe

Haefely Test AG
Birsstrasse 300
4052 Basel
Switzerland
☎ + 41 61 373 4111
☎ + 41 61 373 4912
✉ sales@haefely.com

China

Haefely Test AG Representative Beijing Office
8-1-602, Fortune Street
No. 67, Chaoyang Road, Chaoyang District
Beijing, China 100025
☎ + 86 10 8578 8099
☎ + 86 10 8578 9908
✉ sales@haefely.com.cn

North America

Hipotronics, Inc.
1650 Route 22 N
Brewster, NY 10509
United States
☎ + 1 845 279 3644
☎ + 1 845 279 2467
✉ sales@hipotronics.com